






● contatti utili  
○ contatti casuali

CONTATTI GAMMA	1	3	5	6	9	9	12	12	15	17	19	22	22	25
OC	○		○											○
OM	●	●		●	●	●			●	●	●	●	●	
OL			●	●	●	●					●	●	●	●



OC	OM	OL
1A	1A	1A
2A	2A	2A
3A	3A	3A
4A	4A	4A
5A	5A	5A
6A	6A	6A
7A	7A	7A
8A	8A	8A
9A	9A	9A
10A	10A	10A
11A	11A	11A
12A	12A	12A
13A	13A	13A
14A	14A	14A
15A	15A	15A
16A	16A	16A
17A	17A	17A
18A	18A	18A
19A	19A	19A
20A	20A	20A
21A	21A	21A
22A	22A	22A
23A	23A	23A
24A	24A	24A
25A	25A	25A

AEREO OC  
1.2 0.3 Ω  
3.4 0.1 Ω

AEREO OM  
1.2 0.8 Ω  
3.5 0.8 Ω  
7.8 0.1 Ω

AEREO OL  
1.5 10 Ω  
5.40 0.2 Ω  
4.6 50 Ω

OSC. OC  
7.8 1.3 Ω  
3.40 0.1 Ω  
4.12 0.2 Ω

OSC. OM-OL  
1.2 5.2 Ω  
3.4 0.3 Ω  
5.6 0.7 Ω

FI 1  
2.3 2.2 Ω  
4.5 0.3 Ω

FI 2  
1.2 5 Ω  
2.3 3.5 Ω  
4.6 0.4 Ω

FI 3  
1.2 6.5 Ω  
2.3 2 Ω  
4.5 1.2 Ω

tensioni misurate con voltmetro a 20000 Ω/V  
per batterie a 9V, in assenza di segnale

valori resistivi in Ω, capacitivi in pF,  
salvo indicazioni specifiche

corrente a segnale zero 15 mA  
per 0.2 W d'uscita 65 mA